# INCAIN-LIGHT INSERT RANGE HOOD

**INSERT VENTILATION TO PAIR WITH CURRENT KITCHEN TRENDS.** An elegant, built in flush mounted range hood now with VAM Technology and a depth of 11 1/4" making it an ideal choice for shallow depth cabinetry and perfect for kitchen remodeling projects. The sleek stainless steel panel mounts flush for a clean fully integrated look and can be accented with a liner accessory.



# **AVAILABLE MODELS**

Model #	Size / Color	Choose your own CFM	Sound Levels (sones)
INLT28SSV	28 Stainless	295, 395, 600 CFM	2.8 - 7.5 sones

## Note: Set to 600 CFM motor class out of the box.

## **KEY FEATURES**



### **Backlit Electronic Controls**

Backlit electronic controls with a White LED light to indicate the current speed and LED lighting. Now you can adjust CFM's at installation from the control buttons.



## LED Light Bar

Low consumption 1 watt LED bulbs light up your cooking but use very little energy

## **Perimeter Aspiration**

Air is forced through narrow slots around the perimeter of the center panel greatly improving contaminant extraction.



**Remote Control (INCLUDED)** Control all features of the hood from the convenience of a wireless ADA compliant remote control.

# INCA IN-LIGHT INSERT RANGE HOOD 5 FABER

## DIMENSIONS

## SPECIFICATIONS

cut out dimensions	27 9/16" w x 11 1/4" d		
convertible to ductless / recirculating	yes - with FILTER1		
body depth height	11 1/4"   12 1/8" Yes- (set to 295, 395, 600 CFM)		
Variable Air Management			
controls	4 speed electronic w/ white LED		
lighting	LED light bar		
ducting top	6" round		
grease filters	dishwasher safe mesh		
perimetric filtration system	yes		
10 minute intensive speed	yes		
15 minute auto shut off	yes		
ADA compliant	yes - remote included		
power cord included	yes		
AC power	400 watts / 3.2 amps		

## PERFORMANCE

SPEED	1	2	3	BOOST
CFM	150	295	395	560
Sones	2.8	4.3	6.0	7.5

## ACCESSORIES # FILTER1 -**Charcoal Filter Kit**

High quality charcoal filter for use when recirculating the air back into the kitchen. Filters out odor and should be replaced every 6 months

#### # FILTER1LL -Long Lasting Charcoal **Filter Kit**

New washable charcoal filter can be recharged and washed up to 8 times. For use when recirculating the air back into the kitchen. Filters out odor and can last up to 4 years.

### # LINE3OST / LINE36ST -Stainless Steel Liner 30 & 36"

Create a perfectly-sealed, non- combustible 4" tall perimeter to "line" the wood below the hood. Depth adjustable from 16" - 17 7/8".


### # MUDAMPER6 / MUDAMPER8 -Universal Make-Up Air Damper


Satisfies make-up air requirements, this kit uses an air switch to activate the make-up air damper to open and bring fresh air into the home when the hood fan is on. It then closes tightly when the hood is off. The CFM level is not reduced with this accessory.

#### # WIREBOX -**Fixed Wiring Box**


Replace the power cord with a hard wired box to power the range hood














WARNING! Product specifications are subject to change without notification. Consult the installation instructions before you begin installing this range hood. \* Check local make up air codes for guidelines.

